

**Fifth Semester B.E. Degree Examination, July/August 2022**  
**Digital Signal Processing**

Time: 3 hrs.

Max. Marks: 100

*Note: Answer any FIVE full questions, choosing ONE full question from each module.*

**Module-1**

- 1 a. Obtain a relationship to provide the reconstruction of the periodic signal  $x_p(n)$  from the samples of the spectrum  $X(W)$ . (10 Marks)
- b. Define DFT of a N point sequence  $x(n)$  and IDFT of a N point sequence  $X(K)$ . Let  $x(n)$  is a finite duration sequence of length N or less. Show that  $z\{x(n)\} = X(z)$  can be expressed as a function of  $X(K)$ . (10 Marks)

**OR**

- 2 a. Explain the concept of DFT and IDFT as a linear transformation. Using definition of IDFT, find IDFT of the sequence:  $X(K) = \{6, -2 + 2j, -2, -2 - 2j\}$ . (10 Marks)
- b. By means of DFT and IDFT, determine the sequence  $x_3(n)$  corresponding to the circular convolution of the sequence  $x_1(n)$  and  $x_2(n)$ . Where  $x_1(n) = \{2, 1, 2, 1\}$  and  $x_2(n) = \{1, 2, 3, 4\}$ . (07 Marks)
- c. If  $x(k)$  is the DFT of N point real sequence  $x(n)$ , show that  $X(0)$  is real and  $X\left(\frac{N}{2}\right)$  is real. (03 Marks)

**Module-2**

- 3 a. State and prove time reversal and circular convolution property of DFT. (08 Marks)
- b. The 4 point DFT of a real sequence  $x(n)$  is  $X(K) = \{1, j, 1, -j\}$ . Using properties of DFT, find DFT of the following sequence.
  - i)  $x_1(n) = (-1)^n x(n)$
  - ii)  $x_2(n) = x((n+1))_4$
  - iii)  $x_3(n) = x(4-n)$ . (06 Marks)
- c. With a neat diagram, explain overlap and save method of linear filtering. (06 Marks)

**OR**

- 4 a. Find the output  $y(n)$  of a filter whose impulse response is  $h(n) = \{1, 1, 1\}$  and input signal  $x(n)$  is  $x(n) = \{3, -1, 0, 1, 3, 2, 0, 1, 2, 1\}$  using overlap and add method. (08 Marks)
- b. Prove periodicity and symmetry of twiddle factor. What is in place computation in FFT algorithm? (04 Marks)
- c. Compare computational requirement of direct computation of DFT of a complex valued sequence  $x(n)$  of  $N = 32$  points against FFT algorithm. (08 Marks)

**Module-3**

- 5 a. Find 8-point DFT of the sequence  $x(n) = n + 1; 0 \leq n \leq 7$  using DIF FFT algorithm. (10 Marks)
- b. Develop Radix-2 DIT FFT algorithm for  $N = 8$ . (10 Marks)

OR

- 6 a. Determine 8-point IDFT of the sequence  
 $X(k) = \{6, -0.707 - 1.707j, 1 - j, 0.707 + 0.293j, 0, 0.707 - 0.293j, 1 + j, -0.707 + 1.707j\}$   
 using DIF-FFT algorithm. (10 Marks)
- b. Develop direct form II structure for Goertzel algorithm to find DFT. (10 Marks)

Module-4

- 7 a. Derive an expression to get order  $N$  and cut off frequency  $\Omega_c$  of a analog Butterworth filter. (10 Marks)
- b. Design an analog bandpass filter using Butterworth approximation to meet the following specifications: (10 Marks)
- 3.01dB upper and lower cutoff frequency of 50Hz and 20kHz.
  - Stopband attenuation of atleast 20dB at 20Hz and 45kHz
  - A monotonic frequency response.

OR

- 8 a. A digital Lowpass filter is required to meet the following specifications: (10 Marks)
- Monotonic passband and stopband.
  - 3dB cutoff frequency of  $0.5\pi$  rad.
  - Stopband attenuation of atleast 15dB at  $0.75\pi$  rad.
- Find system function  $H(z)$ . Use Bilinear transformation.
- b. Obtain parallel and cascade realization of the IIR system

$$H(z) = \frac{1 + \frac{1}{3}z^{-1}}{1 - \frac{3}{4}z^{-1} + \frac{1}{8}z^{-2}}$$

(10 Marks)

Module-5

- 9 a. The desired frequency response of a lowpass filter is given by

$$H_d(e^{j\omega}) = H(\omega) = \begin{cases} e^{-j3\omega} & |\omega| < \frac{3\pi}{4} \\ 0 & \frac{3\pi}{4} < |\omega| < \pi \end{cases}$$

Determine the frequency response of the FIR filter if hamming window is used with  $N = 7$ . (10 Marks)

- b. Realize linear-phase FIR filter having the following impulse response

$$h(n) = \delta(n) + \frac{1}{4}\delta(n-1) - \frac{1}{8}\delta(n-2) + \frac{1}{4}\delta(n-3) + \delta(n-4).$$

(05 Marks)

- c. Compare IIR system with FIR system. (05 Marks)

OR

- 10 a. A filter is to be designed with the following desired frequency response:

$$H_d(\omega) = \begin{cases} 0 & -\pi/4 < |\omega| < \pi/4 \\ e^{-j2\omega} & \pi/4 < |\omega| < \pi \end{cases}$$

Find the frequency response of the FIR filter using rectangular window of length  $N = 5$ . (10 Marks)

- b. Consider a 3-stage FIR filter lattice structure having the coefficients  $K_1 = 0.65$ ,  $K_2 = -0.34$  and  $K_3 = 0.8$ . Evaluate its impulse response by tracing a unit impulse  $\delta(n)$  at its input through the lattice structure. Also, draw its direct form structure. (10 Marks)

\*\*\*\*\*