


# CBCS SCHEME



USN

--	--	--	--	--	--	--	--	--	--

15EC52

## Fifth Semester B.E. Degree Examination, June/July 2023 Digital Signal Processing

Time: 3 hrs.

Max. Marks: 80

Note: Answer any FIVE full questions, choosing ONE full question from each module.

### Module-1

- 1 a. Define DFT and IDFT of a signal obtain the relationship between of DFT and  $z$  - transform. (06 Marks)
- b. Compute circular convolution using DFT and IDFT for the following sequences,  $x_1(n) = \{2, 3, 1, 1\}$  and  $x_2(n) = \{1, 3, 5, 3\}$ . (10 Marks)

OR

- 2 a. The first five samples of the 8 - point DFT  $x(k)$  are given as follows :  
 $x(0) = 0.25$ ,  $x(1) = 0.125 - j0.3018$ ,  $x(4) = x(6) = 0$ ,  $x(5) = 0.125 - j0.0518$ . Determine the remaining samples, if the  $x(n)$  is real valued sequence. (04 Marks)
- b. State and prove the circular time shift and circular frequency shift properties. (06 Marks)
- c. If  $x(n) = \{1, 2, 0, 3, -2, 4, 7, 5\}$ , evaluate the following :
- i)  $x(0)$  ii)  $x(4)$  iii)  $\sum_{n=0}^7 x(k)$ . (06 Marks)

### Module-2

- 3 a. Let  $x(n)$  be a finite length sequence with  $X(K) = \{10, 1-j, 4, 1+j\}$ , using properties of DFT, find the DFT of the followings:
- (i)  $x_1(n) = e^{j\frac{\pi}{2}n} x(n)$
- (ii)  $x_2(n) = \left\{ \cos \frac{\pi}{2} n \right\} x(n)$  (08 Marks)
- b. Find the response of an LTI system with an impulse response  $h(n) = \{3, 2, 1\}$  for the input  $x(n) = \{2, -1, -1, -2, -3, 5, 6, -1, 2, 0, 2, 1\}$ , using overlap add method. Use 8-point circular convolution. (08 Marks)

OR

- 4 a. State and prove the,
- (i) Modulation property. (ii) Circular time shift property. (08 Marks)
- b. Consider a finite duration sequence  $x(n) = \{0, 1, 2, 3, 4, 5\}$
- (i) Find the sequence,  $y(n)$  with 6 point DFT is  $y(K) = W_2^K X(K)$ .
- (ii) Determine the sequence  $y(n)$  with 6-point DFT  $y(K) = \text{Real}[X(K)]$ . (08 Marks)

### Module-3

- 5 a. Given  $x(n) = \{1, 0, 1, 0\}$ , find  $x(2)$  using Goertzel algorithm. (06 Marks)
- b. Find the 8-point DFT of the sequence  $x(n) = \{1, 2, 3, 4, 4, 3, 2, 1\}$  using DIT - FFT radix - 2 algorithm. (10 Marks)

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.  
2. Any revealing of identification, appeal to evaluator and/or equations written eg. 42+8 = 50, will be treated as malpractice.

OR

- 6 a. What is chirp-z transform? Mention its applications? (06 Marks)  
 b. Find the 4-point circular convolution of  $x(n)$  and  $h(n)$  give below, using radix-2. DIF-FFT algorithm. (10 Marks)  
 $x(n) = \{1, 1, 1, 1\}$   
 $h(x) = \{1, 0, 1, 0\}$ .

**Module-4**

- 7 a. Design a digital low pass Butterworth Filter using bilinear transformation to meet the following specifications: (10 Marks)  
 $-3 \text{ dB} \leq |H(e^{j\omega})| \leq -1 \text{ dB}$  for  $0 \leq \omega \leq 0.5\pi$   
 $|H(e^{j\omega})| \leq -10 \text{ dB}$  for  $0.7\pi \leq \omega \leq \pi$   
 b. Obtain the parallel form of realization of a system difference equation, (06 Marks)  
 $y(n) = 0.75y(n-1) - 0.125y(n-2) + 6x(n) + 7x(n-1) + x(n-2)$

OR

- 8 a. Convert the analog filter with system function, (08 Marks)  
 $H_a(s) = \frac{s+0.1}{(s+0.1)^2 + 9}$  into a digital IIR filter by means of the impulse invariance method.  
 b. Obtain the DF-I and cascade form of realization of the system function, (08 Marks)  

$$H(z) = \frac{1 + \frac{1}{3}z^{-1}}{\left(1 - \frac{1}{5}z^{-1}\right)\left(1 - \frac{3}{4}z^{-1} + \frac{1}{8}z^{-2}\right)}$$

**Module-5**

- 9 a. Obtain direct form - I, Form - II, Cascade and parallel form of realization for the following System.  $y(n) = 0.75 y(n-1) - 0.125 y(n-2) + 6x(n) + 7x(n-1) + x(n-2)$ . (12 Marks)  
 b. Realize an FIR filter given  $h(n) = \left(\frac{1}{2}\right)^n [u(n) - u(n-4)]$  using direct form - I. (04 Marks)

OR

- 10 a. Write equations of any four different windows used in design of FIR filters. (10 Marks)  
 b. Design the symmetric FIR, lowpass filter whose desired frequency response is given as  

$$H_d(w) = \begin{cases} e^{-jw} & \text{for } |w| \leq w_c \\ 0 & \text{otherwise} \end{cases}$$
  
 The length of the filter should be 7 and  $w_c = 1$  radian/sample use rectangular window. (06 Marks)

\*\*\*\*\*