15AE553 USN

# Fifth Semester B.E. Degree Examination, Dec.2018/Jan.2019 **Theory of Vibrations**

Time: 3 hrs.

Max. Marks: 80

Note: Answer FIVE full questions, choosing ONE full question from each module.

# Module-1

List the types of vibrations and explain any three. 1

(06 Marks)

Derive an expression for work done by Hormonic force.

(04 Marks)

- The motion of a particle is represented by the equation,  $x = 4\sin \omega t$ . Sketch roughly, the variation of the maximum of,
  - (i) Displacement (ii) Velocity
- (iii) Acceleration
- (iv) Jerk

(06 Marks)


- Show that the motion of the piston of an IC engine is periodic with terms containing the fundamental and even harmonics. (10 Marks)
  - Explain Beats phenomenon.

(06 Marks)

3 Derive an expression for natural frequency of an compound pendulum.

(06 Marks) (06 Marks)

Find the mutual frequency of the system shown in Fig. Q3 (b).



Find the mutual frequency of the system shown in Fig. Q3 (c).

(04 Marks)



- Deduce an expression to related vibrational energy and logarithmic decrement. (06 Marks)
  - b. A gun borne / having mass 560 kg is designed with the following data:

Initial recoil velocity: 36 m/sec

Recoil distance: 1.5 m

Calculate: (i) Spring constant

(ii) Damping coefficient

(iii) Time required for the barrel to return to a position of 0.12 m from its initial position.

(10 Marks)

### Module-3

List the service of excitation and explain.

(04 Marks)

Investigate the terms involved in the equations of motion of one DoF system given by,

 $5x + 3x + 12x = 10\sin \omega t$ .

(08 Marks)

Prove that an undamped measuring instrument will show a true response for frequency ratio

$$W_{W_n} = 1/\sqrt{2}$$
.

(04 Marks)

6 a. What is quality factor and half power points and derive an expression for bandwidth.

(08 Marks)


b. A trailer has 1000 kg mass when fully loaded and 250 kg when empty. The spring of the suspension is 350 N/m. The  $\xi=0.5$  when the trailer if full. The speed is 100 km/hr. The road varies sinusoidally with  $\lambda=5$  m. Determine the amplitude ratio of the trailer when fully loaded and empty. (08 Marks)

Module-4

7 a. Derive an expression for natural frequencies of dynamic and static coupling systems.

(10 Marks)

b. Determine the frequency of the system Fig. Q7 (b),  $K_1 = K_2 = 40$  N/m, K = 60 N/m,  $m_1 = m_2 = 10$  kg (06 Marks)



8 a. With a neat sketch, explain Lanchester Damper and Houdaille damper.

(10 Marks)


b. Derive ID wave equation for transverse vibration of beams.

(06 Marks)

## Module-5

OR

9 a. Find the first natural frequency of the system by matrix iteration method. (10 Marks)



b. Determine the natural frequencies of the system.

(06 Marks)




Fig. Q9 (b)

OR

Find the natural frequency by Holzer method,  $m_1 = m_2 = m_3 = 1$  kg,  $K_1 = K_2 = K_3 = 1$  N/m (16 Marks)




Fig O10

2 of 2