

CBCS SCHEME

USN
Learning Resource Centre
Acharya Institute & Technology

| | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|
| | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|

17CS753

Seventh Semester B.E. Degree Examination, Feb./Mar. 2022 Digital Image Processing

Time: 3 hrs.

Max. Marks: 100

Note: Answer any FIVE full questions, choosing ONE full question from each module.

Module-1

- 1 a. Consider an image segment $V = \{1, 2\}$, shown below, compute the lengths of shortest 4, 8 and m path between 'p' and 'q'. If path does not exist between 'p' and 'q' explain why?
- | | | | | | |
|-----|---|---|---|---|-----|
| | 3 | 1 | 2 | 1 | (q) |
| | 2 | 2 | 0 | 2 | |
| | 1 | 2 | 1 | 1 | |
| (p) | 1 | 0 | 1 | 2 | |
- (08 Marks)
- b. Explain steps in image processing with neat diagram. (08 Marks)
- c. Let 'P' and 'Q' are two pixels at coordinates (100, 120) and (130, 160) respectively. Find : (i) Chess board (ii) City Block distance. (04 Marks)

OR

- 2 a. Define 4 adjacency, 8 adjacency and m adjacency. (06 Marks)
- b. Explain the applications of image processing. (08 Marks)
- c. Let the set of gray levels to define connectivity be {94, 95, 96, 97} and compute the shortest D_4 and D_8 distances between pixels p and q for the given image.
- | | | | | |
|-----|----|----|-----|----|
| (P) | 96 | 97 | 94 | 97 |
| | 98 | 98 | 100 | 96 |
| | 99 | 97 | 98 | 95 |
| (Q) | 97 | 96 | 97 | 96 |
- (06 Marks)

Module-2

- 3 a. Explain applications of arithmetic and Logical operations in digital image processing. (08 Marks)
- b. Apply histogram mapping to the following image (8*8)
- | | | | | | | | | |
|-------|---|----|----|---|----|----|---|---|
| R_K | 0 | 1 | 2 | 3 | 4 | 5 | 6 | 7 |
| P_K | 8 | 10 | 10 | 2 | 12 | 16 | 4 | 2 |
- Target histogram is given below
- | | | | | | | | | |
|-------|---|---|---|---|----|----|----|---|
| R_K | 0 | 1 | 2 | 3 | 4 | 5 | 6 | 7 |
| P_K | 0 | 0 | 0 | 0 | 20 | 20 | 16 | 8 |
- (08 Marks)
- c. Explain vector representation of linear filtering. (04 Marks)

OR

- 4 a. Perform histogram equalization of an image whose pixel intensity distribution is given below:

| | | | | | | | | |
|--------------|-----|------|-----|-----|-----|-----|-----|----|
| Gray Levels | 0 | 1 | 2 | 3 | 4 | 5 | 6 | 7 |
| No. of Pixel | 790 | 1023 | 850 | 656 | 329 | 245 | 122 | 81 |

(08 Marks)

- b. Explain the following transformation:
 i) Contrast stretching
 ii) Intensity level slicing
 iii) Bit plan slicing.
- c. Explain the use of image negatives.

(08 Marks)
 (04 Marks)

Module-3

- 5 a. Apply Discrete Fourier transform for the following image

| | | | |
|---|---|---|---|
| 2 | 0 | 0 | 0 |
| 0 | 0 | 0 | 0 |
| 0 | 0 | 0 | 0 |
| 0 | 0 | 0 | 0 |

(08 Marks)

- b. Explain the properties of 2D Discrete Fourier Transform is frequency domain filtering.
 (08 Marks)
- c. Explain Bandpass filter is Notch filter.
 (04 Marks)

OR

- 6 a. Explain 2D convolution theorem of Discrete Fourier Transform frequency domain filtering.
 (10 Marks)
- b. Find the DFT of the following sequence using matrix and verify whether DFT works correctly $X = \{1, 2, 8, 9\}$.
 (10 Marks)

Module-4

- 7 a. Explain Local processing in edge linking.
 (10 Marks)
- b. Explain Otsu's method used in image segmentation.
 (10 Marks)

OR

- 8 a. Explain Hough transform in edge linking.
 (10 Marks)
- b. Explain region splitting and merging algorithm with example image.
 (10 Marks)

Module-5

- 9 a. Code the following message using arithmetic coding algorithm. "SWISS"
 (10 Marks)
- b. Code the message "ABBABAS" using LZW and encode the same.
 (10 Marks)

OR

- 10 a. Construct arithmetic coding for the string CBAC using the following table :

| | | | |
|-------------|-----|-----|-----|
| Symbol | A | B | C |
| Probability | 0.3 | 0.3 | 0.4 |

(10 Marks)

- b. Compress the following 8 bit image using Huffman coding.

| | | | | | | | |
|----|----|----|----|-----|-----|-----|-----|
| 21 | 21 | 21 | 95 | 169 | 243 | 243 | 243 |
| 21 | 21 | 21 | 95 | 169 | 243 | 243 | 243 |
| 21 | 21 | 21 | 95 | 169 | 243 | 243 | 243 |
| 21 | 21 | 21 | 95 | 169 | 243 | 243 | 243 |

(10 Marks)
