

CBCS SCHEME

USN

17EE45

Fourth Semester B.E. Degree Examination, Jan./Feb. 2023

Electromagnetic Field Theory

Time: 3 hrs.

Max. Marks: 100

Note: Answer any FIVE full questions, choosing ONE full question from each module.

Module-1

- For a vector field defined by the equations, $\vec{F} = x^2y\hat{a}_x + 2z\hat{a}_y + xy2\hat{a}_z$. Find the curve of \vec{F} . (08 Marks)
 - Transform the vector $10\hat{a}_x$ at $P(x = -3, y = 2$ and $z = 4)$ to spherical coordinates. (06 Marks)
 - A charge $Q_2 = 121 \times 10^{-9}C$ is located in vacuum at $P_2(-0.03, 0.01, 0.04)m$. Find the force on Q_2 due to $Q_1 = 110 \mu c$ at $P_1(0.03, 0.08, -0.02)m$. (06 Marks)

OR

- Two points $A(2, 2, 1)$ and $B(3, -4, 2)$ are given in the Cartesian system. Obtain the vector from A to B and a unit vector directed from A to B. (06 Marks)
 - Two small identical conducting spheres have charges of $2nc$ and $-1nc$ respectively. When they are separated by 4 cm apart, find the magnitude of the force between them. If they are brought into contact and then again separated by 4cm, find the force between them. (06 Marks)
 - If $\vec{D} = xy^2z^2\hat{a}_x + x^2yz^2\hat{a}_y + x^2y^2z\hat{a}_z$ c / m²,
Find :
 - An expression for ρ_v
 - The total charge will in the cube where cube is defined by $0 \leq x \leq 2, 0 \leq y \leq 2, 0 \leq z \leq 2$. (08 Marks)

Module-2

- Given that the potential field is $V = 2x^2y - 5z$, find the potential, electric field intensity and volume charge density at point $P(-4, 3, 6)$. (08 Marks)
 - At the boundary between glass ($\epsilon_r = 4$) and air, the lines of electric field make an angle of 40° with normal to the boundary. If electric flux density in the air is $0.25\mu c/m^3$, determine the orientation and magnitude of electric flux density in the glass. (06 Marks)
 - Derive the continuity equation in point and integral forms. (06 Marks)

OR

- Find the total current in outward direction form a cube of 1m, with one corner at the origin and edges parallel to the coordinate axes, if $\vec{J} = 2x^2\hat{a}_x + 2xy^3\hat{a}_y + 2xy\hat{a}_z$ A / m². (08 Marks)
 - Determine the capacitance of a capacitor consisting of two parallel plates 30cm \times 30cm surface area, separated by 5mm in air. What is the total energy stored by the capacitor is charged to a potential difference of 500V? What is the energy density? (07 Marks)
 - An electric potential is given by $V = \frac{60\sin\theta}{r^2}$ V. Find V and \vec{E} at $P(3, 60^\circ, 25^\circ)$. (05 Marks)

Module-3

- 5 a. State and prove Uniqueness Theorem. (10 Marks)
 b. Determine whether or not the potential equations :
 i) $V = 2x^2 - 4y^2 + z^2$
 ii) $V = r^2 \cos \phi + \theta$
 Satisfy the Laplace's equation. (05 Marks)
 c. List the Maxwell's equation in point and integral forms. (05 Marks)

OR

- 6 a. State and prove Biot Savart law. (06 Marks)
 b. Find the magnetic flux density at the centre 'O' of a square of sides equal to 5m and carrying 10 amperes of current. (10 Marks)
 c. Define scalar and vector magnetic potentials. (04 Marks)

Module-4

- 7 a. A point charge, $Q = -60 \text{ nc}$ is moving with a velocity of $6 \times 10^6 \text{ m/s}$ in the direction specified by unit vector $-0.48\hat{a}_x - 0.6\hat{a}_y + 0.64\hat{a}_z$. Find the magnitude of the force on a moving charge in the magnetic field. $B = 2\hat{a}_x - 6\hat{a}_y + 5\hat{a}_z \text{ mT}$. (06 Marks)
 b. Find the magnitude of magnetic flux density in a material for which
 i) The magnetization is 2.8 A/m, the magnetic susceptibility is 0.0025
 ii) The magnetic field intensity is 1300 A/m and the relative permeability is 1.006. (06 Marks)
 c. Find the normal component of the magnetic field which traverses from medium -1 to medium -2 having $\mu_{r1} = 2.5$ and $\mu_{r2} = 4$. Given that $\vec{H} = -30\hat{a}_x + 50\hat{a}_y + 70\hat{a}_z \text{ V/m}$ in medium -1 and the interface of the two media is $x - y$ plane. (08 Marks)

OR

- 8 a. Find the magnetic field intensity inside a magnetic material, for the following conditions.
 $M = 100 \text{ A/m}$ and $\mu = 1.5 \times 10^{-5} \text{ H/m}$
 $B = 200 \mu\text{T}$, $\chi_m = 15$. (06 Marks)
 b. A air core toroid has a mean radius of 40mm and is wound with 4000 turns of wire. The circular cross-section of the toroid has a radius of 4mm. A current of 10A is passed in the wire. Find the inductance and the energy stored. (06 Marks)
 c. A rectangular coil as shown below is in the magnetic field given by $\vec{B} = 0.05 \frac{\hat{a}_x + \hat{a}_y}{\sqrt{2}} \text{ T}$. Find the torque about Z-axis when the coil is in position shown in Fig.Q8(c) and carries a current of 5A.




Fig.Q8(c)

2 of 3

(08 Marks)

Module-5

- 9 a. For a lossy electric, $\sigma = 5 \text{ S/m}$ and $\epsilon_r = 1$. The electric field intensity is $E = 100 \sin 10^{10}t$. Find J_C , J_D and frequency at which both have equal magnitudes. (08 Marks)
- b. Determine :
- Attenuation constant
 - Phase constant
 - Propagation constant
 - Wave length
 - Phase velocity
 - Intrinsic impedance
- For damp soil of frequency of 1 MHz given that $\epsilon_r = 12$, $\mu_r = 1$ and conductivity $\sigma = 20 \times 10^{-3} \text{ S/m}$. (06 Marks)
- c. The depth of penetration in a certain conducting medium is 0.1m and the frequency of electromagnetic wave is 1.0 MHz. Find the conductivity of the conducting medium. (06 Marks)

OR

- 10 a. Find the displacement current density within a parallel plate capacitor having a dielectric with $\epsilon_r = 10$, area of plates $A = 0.01 \text{ m}^2$, distance of separation $d = 0.05 \text{ mm}$. Applied voltage is $V = 200 \sin 200t$. (08 Marks)
- b. A 800 MHz plane wave travelling has an average pointing vector of 8 MW/m^2 . If the medium is losses with $\mu_r = 1.5$ and $\epsilon_r = 6$. Find :
- Velocity of wave
 - Wave length
 - Impedance of the medium
 - rms electric field E
 - rms magnetic field H.
- (12 Marks)
