



# CBCS SCHEME

USN

--	--	--	--	--	--	--	--	--	--

18EE55

## Fifth Semester B.E. Degree Examination, Dec.2023/Jan.2024 Electrical Machine Design

Time: 3 hrs.

Max. Marks: 100

*Note: Answer any FIVE full questions, choosing ONE full question from each module.*

### Module-1

- 1 a. List and explain the factors to be considered during the design of electrical machines. (08 Marks)
- b. List and explain the limitations in design. (08 Marks)
- c. Explain the Modern Machine Manufacturing Techniques. (04 Marks)

OR

- 2 a. List the different types of materials used in electrical machines. Explain the classification of insulating materials. (10 Marks)
- b. What is design and why design is required? (04 Marks)
- c. List the additional factors to be considered while designing electrical machines. (06 Marks)

### Module-2

- 3 a. Derive an expression for the output equation of a DC machine. (10 Marks)
- b. A design is required for a 50 KW, 4 pole, 600 rpm, dc shunt generator, with a terminal voltage of 220 V. If maximum gap density is  $0.83 \text{ Wb/m}^2$  and the armature ampere conductors/meter are 30,000. Calculate the suitable dimensions of armature core to give a square pole face. Assume that full load armature voltage drop is 3% of rated terminal voltage and that of field current is 1% of rated full load current. Ratio of pole arc to pole pitch is 0.67. (10 Marks)

OR

- 4 a. List and explain the factors to be considered while selecting number of poles of a DC machine. (06 Marks)
- b. Show that the output of a DC generator with single turn coil is given by the expression  $P' = \frac{0.03E'VqA}{PN} \text{ kW}$  where  $E'$  = Average voltage between adjacent commutator segment,  $V$  = peripheral speed of generator in m/sec. (10 Marks)
- c. What are the advantages of large number of poles in a D.C. machine? (04 Marks)

### Module-3

- 5 a. Derive an expression for output equation of single phase transformer. (10 Marks)
- b. Find the main dimensions of a core and window for a 500 KVA, 6600/400 V, 50 Hz,  $1\phi$ , transformer. Assume the flux density of  $2.75 \text{ A/mm}^2$ . Window space factor is 0.32, volt/turn is 16.8 Volts. Use cruciform core section. Height of the window is 3 times its width. Also find cross sectional area of primary and secondary winding. (10 Marks)

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.  
2. Any revealing of identification, appeal to evaluator and /or equations written eg, 42+8 = 50, will be treated as malpractice.



OR

- 6 a. Calculate the no load current for 11000/400 V, 50 Hz,  $1\phi$ , core type transformer. If mean length of magnetic path is 300 cm, gross iron area of the core  $150 \text{ cm}^2$ , maximum flux density is 1.2 Tesla, core loss/kg of iron is 3.3 Watts. Ampere turns/metre of the transformer iron is 800, density of iron is 7.5 g/cc. Stacking factor of iron is 0.95 and joints are equivalent 0.1 mm of air gap. (12 Marks)
- b. Derive an expression for output equation of a three phase transformer. (08 Marks)

Module-4

- 7 a. Discuss the various factors that affect the choice of the length of air gap of an induction motor. (08 Marks)
- b. Determine the diameter and length of stator core of a 70 HP, 415 V,  $3\phi$ , 50 Hz, star connected, 6 pole induction motor. The specific electric and magnetic loadings are 32000 Ampere conductors/metre and  $0.51 \text{ Wb/m}^2$ . Take efficiency as 90% and power factor as 0.91. Assume number of slots/pole/phase as 3 and pole pitch is equal to core length. Estimate the number of stator conductors required for the winding in which conductors are connected in two parallel paths. Choose a suitable number of conductors/slot so that the slot loading does not exceed 750 Ampere-conductor. Take slot pitch as 1.5 to 2.5 cm. (12 Marks)

OR

- 8 a. With a neat diagram, explain the crawling and cogging of an induction motor. (10 Marks)
- b. Discuss in detail the calculation of no load current of a 3 phase induction motor. (10 Marks)

Module-5

- 9 a. Derive an expression for output equation of a three phase synchronous machine. (10 Marks)
- b. Determine suitable dimensions for a 500 kVA, 50 Hz,  $3\phi$ , alternator to run at 375 rpm. Mean gap density over a pole pitch is 0.55 tesla and specific electric loading is 250 ampere conductor/cm. The peripheral speed not to exceed 30 m/sec. Assume armature winding is full pitched with a phase spread of  $60^\circ$ . Take  $\frac{L}{\tau}$  ratio as 1. (10 Marks)

OR

- 10 a. With a graph, explain short circuit ratio and explain the effect of SCR on machine performance. (08 Marks)
- b. A 3 phase, 30 pole, 3.3 KV, Y connected salient pole alternator is designed to supply a rated current of 130 A, with average flux density of 0.55 Tesla. The specific electric loading is 3000 Ampere conductors/metre. If the conductors/slot is 9 and slots/pole/phase is 2, find kVA rating of alternator, main dimensions, width of parallel slots, if the flux density in tooth is 1.8 Tesla. Take  $K_p$  as 1,  $K_w = 0.955$  and ratio of  $\frac{L}{\tau} = 5$ . Also take stacking factor as 0.9,  $n_v$  as 4 and  $b_v$  as 1 cm. (12 Marks)

\*\*\*\*\*