



Fourth Semester B.E. Degree Examination, June/July 2024  
**Engineering Statistics and Linear Algebra**

Time: 3 hrs.

Max. Marks: 100

Note: Answer any FIVE full questions, choosing ONE full question from each module.

### Module-1

- 1 a. Derive mean, variance and characteristic function for uniformly distributed random variable. (10 Marks)
- b. The cdf for random variable  $z$  is  $F_z(z) = \begin{cases} 1 - \exp(-2z^{3/2}) & z \geq 0 \\ 0 & \text{otherwise} \end{cases}$   
Evaluate  $P(0.5 < z \leq 0.9)$  (04 Marks)
- c. It is given that  $E[X] = 2$  and  $E[X^2] = 6$ .  
(i) Find standard deviation of  $X$ .  
(ii) If  $Y = 6X^2 + 2X - 13$ . Find mean of  $Y$ . (06 Marks)

OR

- 2 a. Given the data in the following table:
- | K        | 1    | 2    | 3    | 4    | 5    |
|----------|------|------|------|------|------|
| $x_K$    | 2.1  | 3.2  | 4.8  | 5.4  | 6.9  |
| $p(x_K)$ | 0.21 | 0.18 | 0.20 | 0.22 | 0.19 |
- (i) Plot pdf and cdf of discrete random variable  $X$ .  
(ii) Write expression for  $f_X(x)$  and  $F_X(x)$  using unit delta functions and unit step functions. (08 Marks)
- b. The random variable  $X$  is uniformly distributed between 0 and 2.  $Y = 3x^3$ . What is the pdf of  $X$ ? (06 Marks)
- c. The random variable  $X$  is uniformly distributed between 0 and 5. The event  $B = \{X > 3.7\}$ . What are  $f_{X/B}(x)$ ,  $\mu_{X/B}$  and  $\sigma_{X/B}^2$ ? (06 Marks)

### Module-2

- 3 a. A bivariate Pdf is given as  $f_{XY}(x, y) = 0.2\delta(x)\delta(y) + 0.3\delta(x-1)\delta(y) + 0.3\delta(x)\delta(y-1) + C\delta(x-1)\delta(y-1)$   
i) What is the value of the constant  $C$ ?  
ii) What are the Pdfs for  $X$  and  $Y$ ?  
iii) What is  $F_{XY}(x, y)$  when  $(0 < x < 1)$  and  $(0 < y < 1)$ ?  
iv) What are  $F_{XY}(x, \alpha)$  and  $F_{XY}(\alpha, y)$ ?  
v) Are  $X$  and  $Y$  independent? (08 Marks)
- b. The mean and variance of random variable  $X$  are -1 and 2. The mean and variance of random variable  $Y$  are 3 and 4. The correlation coefficient  $\rho_{XY} = 0.5$ . What are the covariance  $COV[XY]$  and the correlation  $E[XY]$ . (05 Marks)
- c. Write a short note on Chi-square random variable and students random variable. (07 Marks)

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.  
2. Any revealing of identification, appeal to evaluator and/or equations written eg.  $42+8 = 50$ , will be treated as malpractice.

OR

- 4 a. X is a random variable,  $\mu_X = 4$  and  $\sigma_X = 5$ , Y is a random variable,  $\mu_Y = 6$  and  $\sigma_Y = 7$ . The correlation coefficient is 0.2. If  $U = 3X + 2Y$ . What are  $\text{var}[u]$ ,  $\text{cov}[uX]$  and  $\text{cov}[uY]$ ? (08 Marks)

Let 'X' and 'Y' be exponentially distributed random variable with  $f_X(x) = \begin{cases} \lambda e^{-\lambda x} & x \geq 0 \\ 0 & x < 0 \end{cases}$

- b. Obtain the characteristic function and Pdf of  $W = X + Y$ . (06 Marks)
- c. The Random variables  $X_i$  have same mean of  $m_x = 4$  and variance of  $\sigma_x^2 = 1.5$ . For  $w = \sum_{i=1}^{150} X_i$ , determine  $m_w$  and  $\sigma_w^2$ . Also for  $w = \frac{1}{150} \sum_{i=1}^{150} X_i$ , determine  $m_y$  and  $\sigma_y^2$ . Comment on the result. (06 Marks)

**Module-3**

- 5 a. Define the following:  
 (i) Random processes (04 Marks)  
 (ii) Stationary processes. (06 Marks)
- b. Write the properties of Autocorrelation function. (06 Marks)
- c. Show that the random process  $X(t) = A \cos(\omega_c t + \theta)$  is wide sense stationary. 'θ' is uniformly distributed in the range  $-\pi$  to  $\pi$ . (10 Marks)

OR

- 6 a. For the random process  $X(t) = A \cos(\omega_c t + \theta)$ , A and  $\omega_c$  are constants. θ is a random variable, uniformly distributed between  $\pm \pi$ . Show that this process is ergodic. (08 Marks)
- b. Determine the power spectral density of the random process  $X(t) = A \cos(\omega_c t + \theta)$  and plot the same. Here θ is random variable uniformly distributed over 0 to  $2\pi$ . Hence obtain average power of X(t). If the frequency becomes zero,  $X(t) = A$  i.e. a d.c. signal, then obtain power spectral density and autocorrelation function. (08 Marks)
- c. A wide sense stationary random process X(t) is applied to a LTI system with impulse response  $h(t) = ae^{-at}u(t)$ . Find the mean value of the output Y(t) of the system if  $E[X(t)] = 6$  and 'a' = 2. (04 Marks)

**Module-4**

- 7 a. Write the complete solution as  $x_p +$  multiplies of s in the null space.  
 $x + 3y + 3z = 1$   
 $2x + 6y + 9z = 5$   
 $-x - 3y + 3z = 5$  (06 Marks)
- b. Find bases for the four subspaces associated with  $A = \begin{bmatrix} 1 & 2 & 4 \\ 2 & 4 & 8 \end{bmatrix}$ . (04 Marks)
- c. Find orthogonal vector A, B and orthonormal vector  $q_1$   $q_2$  from a, b using Gram Schmidt process. Factorize into  $A = QR$ .  $a = \begin{bmatrix} 1 \\ 1 \end{bmatrix}$ ,  $b = \begin{bmatrix} 4 \\ 0 \end{bmatrix}$ . (10 Marks)

OR

- 8 a. Reduce A to echlon form. Which combination of rows of A produce zero row? What is the left Null space?

$$A = \begin{bmatrix} 1 & 2 & b_1 \\ 3 & 4 & b_2 \\ 4 & 6 & b_3 \end{bmatrix}$$

(04 Marks)

- b. Project the vector b onto the line through a. Check that e is perpendicular to a.

$$b = \begin{bmatrix} 1 \\ 2 \\ 2 \end{bmatrix}, \quad a = \begin{bmatrix} 1 \\ 1 \\ 1 \end{bmatrix}$$

(08 Marks)

- c. In order to fit best straight line through four points passing through  $b = 0, 8, 8, 20$  at  $t = 0, 1, 3, 4$ . Set up and solve normal equations  $A^T A \hat{x} = A^T b$ .

(08 Marks)

Module-5

- 9 a. Mention the properties of determinants.

(08 Marks)

- b. If  $A = \begin{bmatrix} 3 & -1 & 1 \\ -1 & 5 & -1 \\ 1 & -1 & 3 \end{bmatrix}$ , show that matrix A is positive definite matrix.

(06 Marks)

- c. Find the eigen values of  $A = \begin{bmatrix} 2 & 3 \\ 3 & -6 \end{bmatrix}$ .

(06 Marks)

OR

- 10 a. Diagonalize the following matrix, if possible  $A = \begin{bmatrix} 1 & 3 & 3 \\ -3 & -5 & -3 \\ 3 & 3 & 1 \end{bmatrix}$ .

(10 Marks)

- b. Find a singular value of decomposition of,  $A = \begin{bmatrix} 1 & -1 \\ -2 & 2 \\ 2 & -2 \end{bmatrix}$ .

(10 Marks)

\*\*\*\*\*